

**STERILIZATION SYSTEM EMPLOYING A SWITCHING MODULE
ADAPTED TO PULSATE THE LOW FREQUENCY POWER APPLIED TO A
PLASMA**

5

Claim of Priority

This application is a continuation-in-part of and claims priority from U.S. Utility Patent Application No. 09/677,534, filed October 2, 2000.

10

Background of the Invention

Field of the Invention

The invention relates to systems and methods for controlling gas discharge plasmas in sterilization systems that employ gas discharge plasmas.

Description of the Related Art

15

Plasmas produced using radio frequency (RF) generators in particular have proven to be valuable tools in processes for the sterilization of medical devices. For example, in U.S. Patent Nos. 4,643,876 and 4,756,882, which are incorporated by reference herein, Jacobs, et al. disclose using hydrogen peroxide as a precursor in a low temperature sterilization system that employs RF plasma. The combination of hydrogen peroxide vapor and a RF plasma provides an efficient method of sterilizing medical devices without using or leaving highly toxic materials or forming toxic by-products. Similarly, Jacob, U.S. Patent No. 5,302,343, and Griffiths, et al., U.S. Patent No. 5,512,244, teach the use of RF plasmas in a sterilization process.

20

25

30

However, there are problems associated with the use of an RF plasma in a sterilization process. The RF plasma may leave residual hydrogen peroxide on the sterilized article. The residual amount of hydrogen peroxide remaining on the sterilized article depends upon the RF power applied to the article, the amount of time exposed to the RF plasma, and the material of the article. For example, while some plastics (e.g., polyurethane) absorb hydrogen peroxide, other materials (e.g., Teflon) absorb relatively little, thereby yielding less residual hydrogen peroxide after sterilization.

In addition, inherent inefficiencies in the energy conversion from the low frequency (*e.g.*, 60 Hz) line voltage to the RF (*e.g.*, approximately 1 MHz - 1 GHz) voltage used to generate the RF plasma limit the power efficiency of such systems to typically less than 50%. Energy efficiency is further reduced by typically 5 - 20% by virtue of the losses from the required impedance matching network between the RF generator and the load. Such low energy efficiency significantly increases the cost per watt applied to the sterilized articles. The required instrumentation for using RF electrical energy (*e.g.*, RF generator, impedance matching network, monitoring circuitry) is expensive, which also increases the cost per watt applied to the sterilized articles.

Summary of the Invention

One aspect of the present invention is a sterilization system that applies low frequency power to a plasma within a vacuum chamber to remove gas or vapor species from an article. The low frequency power has a frequency less than or equal to approximately 200 kHz. The sterilization system comprises a switching module adapted to pulsate the low frequency power applied to the plasma. The sterilization system further comprises a low frequency power feedback control system for controllably adjusting the low frequency power applied to the plasma. The low frequency power feedback control system comprises a power monitor adapted to produce a first signal indicative of the low frequency power applied to the plasma within the vacuum chamber. The low frequency power feedback control system further comprises a power control module adapted to produce a second signal in response to the first signal from the power monitor, and a power controller adapted to adjust, in response to the second signal, the low frequency power applied to the plasma to maintain a substantially stable average low frequency power applied to the plasma while the article is being processed.

Another aspect of the present invention is a method of controllably adjusting a low frequency power applied to a plasma within a vacuum chamber of a sterilization system to remove gas or vapor species from an article. The low frequency power has a frequency less than or equal to approximately 200 kHz. The method comprises

pulsating the low frequency power applied to the plasma and monitoring the low frequency power applied to the plasma within the vacuum chamber. The method further comprises generating a first signal indicative of the low frequency power applied to the plasma. The method further comprises adjusting the low frequency power applied to the plasma in response to the first signal to maintain a substantially stable average low frequency power applied to the plasma while the article is being processed.

Brief Description of the Drawings

Figure 1 schematically illustrates a preferred embodiment of a sterilization system compatible with the present invention.

Figure 2A schematically illustrates a preferred embodiment of a cylindrically-shaped electrode with open ends and perforated sides.

Figure 2B schematically illustrates an alternative embodiment of a cylindrically-shaped electrode with open ends and louvered sides.

Figure 2C schematically illustrates an alternative embodiment of a cylindrically-shaped electrode with open ends and solid sides.

Figure 2D schematically illustrates an alternative embodiment of an electrode comprising one or more colinear cylindrically-shaped segments with open ends and solid sides.

Figure 2E schematically illustrates an alternative embodiment of an electrode with a partial cylindrical shape, open ends, and solid sides.

Figure 2F schematically illustrates an alternative embodiment of a cylindrically-symmetric and longitudinally-asymmetric electrode with open ends and solid sides.

Figure 2G schematically illustrates an alternative embodiment of one or more asymmetric electrodes with open ends and solid sides.

Figure 2H schematically illustrates an alternative embodiment of an electrode system with a first electrode that is cylindrically-shaped with open ends and solid sides, and a second electrode comprising a wire substantially colinear with the first electrode.

Figure 2I schematically illustrates an alternative embodiment of a generally square or rectangular electrode within a generally square or rectangular vacuum chamber.

Figure 3, which is broken into Figures 3A and 3B, schematically illustrates an embodiment of a low frequency power module compatible with the phase angle control method of the present invention.

Figure 4, which is broken into Figures 4A and 4B, schematically illustrates an embodiment of a low frequency power module compatible with the amplitude control method of the present invention.

Figure 5A schematically illustrates the phase angle control method of controlling the low frequency power applied to the plasma.

Figure 5B schematically illustrates the amplitude control method of controlling the low frequency power applied to the plasma.

Figure 6, which is broken into Figures 6A and 6B, schematically illustrates an embodiment of a low frequency power module comprising a switching module compatible with the present invention.

Figure 7 schematically illustrates the output from a switching module compatible with the present invention which pulsates an incoming sinusoidal voltage with a frequency of 60 Hz to form a series of voltage pulses with widths W and spaced by times T .

Figure 8A schematically illustrates a rippled DC voltage generated by full-wave-rectifying and filtering the line voltage prior to pulsating the voltage via the switching module.

Figure 8B schematically illustrates the rippled DC voltage of Figure 8A after being pulsated by the switching module utilizing unipolar switching.

Figure 8C schematically illustrates the rippled DC voltage of Figure 8A after being pulsated by the switching module utilizing bipolar switching.

Figure 9 schematically illustrates one embodiment of a switching module which generates a unipolar pulsation.

Figure 10 schematically illustrates a preferred embodiment of a method of sterilization compatible with the present invention.

Detailed Description of the Preferred Embodiment

Production of gas discharge plasmas using low frequency (LF) voltages avoids the various problems inherent in the state of the art sterilization devices and processes

which form and use plasmas produced by radio frequency (RF) voltages. First, LF plasma processing leaves less residual reactive species remaining on the sterilized articles than does RF plasma processing. Second, generation of the LF plasma is highly energy efficient because little or no frequency conversion from the line voltage is needed. For example, by using no frequency conversion with a line voltage frequency of 60 Hz, the energy efficiency of the sterilization system can reach approximately 85-99%. Use of LF voltages also does not require an impedance matching network, thereby avoiding the associated energy losses. Third, due to the simplified instrumentation and higher energy efficiency of LF generation, the cost per watt applied to the sterilized articles using LF plasmas can be as low as one-tenth the cost per watt of using RF plasmas. Fourth, the simplified instrumentation used for generating LF plasmas has proven to be more reliable and robust, and requiring less complicated diagnostic instrumentation.

Figure 1 schematically illustrates one preferred embodiment of the present invention comprising a sterilization system 10. The sterilization system 10 comprises a vacuum chamber 12, a vacuum pump 14, a vacuum pump line 15, a vacuum pump valve 16, a reactive agent source 18, a reactive agent line 19, a reactive agent valve 20, a low frequency (LF) power module 22, an LF voltage conduit 24, a vent 26, a vent line 27, a vent valve 28, a process control module 30, an electrode 32, and a reactive agent monitor 34. Persons skilled in the art recognize that other embodiments comprising sterilization systems of different configurations than that illustrated in Figure 1 are compatible with the present invention.

In the preferred embodiment of the present invention, the articles (not shown in Figure 1) to be sterilized are packaged in various commonly employed packaging materials used for sterilized products. The preferred materials are spunbonded polyethylene packaging material commonly available under the trademark "TYVEK" or composites of "TYVEK" with a polyethylene terephthalate packaging material commonly available under the trademark "MYLAR". Other similar packaging materials may also be employed such as polypropylene. Paper packaging materials may also be used. With paper packaging, longer processing times may be required to achieve sterilization because of possible interactions of the reactive agent with paper.

The vacuum chamber 12 of the preferred embodiment is sufficiently gas-tight to support a vacuum of approximately less than 40 Pa (0.3 Torr). Coupled to the vacuum chamber 12 is a pressure monitor (not shown) which is also coupled to the process control module to provide a measure of the total pressure within the vacuum chamber. Also coupled to the vacuum chamber 12 is the reactive agent monitor 34 which is capable of detecting the amount of the reactive agent in the vacuum chamber 12. In the exemplary embodiment of the present invention, the reactive agent is hydrogen peroxide, and the reactive agent monitor 34 measures the absorption of ultraviolet radiation at a wavelength characteristic of hydrogen peroxide. Other methods of reactive agent detection compatible with the present invention include, but are not limited to, pressure measurement, near infrared absorption, and dew point measurement. The reactive agent monitor 34 is also coupled to the process control module 30 to communicate the detected amount of the reactive agent to the process control module 30.

In the preferred embodiment of the present invention, inside and electrically isolated from the vacuum chamber 12 is the electrode 32, which is electrically conductive and perforated to enhance fluid communication between the gas and plasma species on each side of the electrode 32. The electrode 32 of the preferred embodiment generally conforms to the inner surface of the vacuum chamber 12, spaced approximately one-half to two inches from the wall of the vacuum chamber 12, thereby defining a gap region between the vacuum chamber 12 and the electrode 32. The electrode 32 is coupled to the LF power module 22 via the LF voltage conduit 24. In the preferred embodiment, with the vacuum chamber 12 connected to electrical ground, application of an LF voltage between the vacuum chamber 12 and the electrode 32 creates an LF electric field which is stronger in a first region 31 which includes the gap region and the vicinity of the edges of the electrode 32. The LF electric field is weaker in a second region 33 where the sterilized articles are placed. Generally, in other embodiments, the LF electric field can be generated by applying an LF voltage between the electrode 32 and a second electrode in the vacuum chamber 12. In such embodiments, the first region 31 includes the gap region between the two electrodes, and the vicinity of the edges of one or both of the electrodes. The preferred

embodiment in which the vacuum chamber 12 serves as the second electrode is one of the many different ways to generate the gas plasma.

In the preferred embodiment illustrated in Figure 2A, a cylindrically-shaped electrode 32 provides fluid communication between the gas and plasma on each side of the electrode 32 through the open ends of the electrode 32 as well as through the perforations in the side of the electrode 32. These open ends and perforations permit gaseous and plasma species to freely travel between the first region 31 between the electrode 32 and the walls of the vacuum chamber 12 and the second region 33 where the sterilized articles are placed. Similarly, as illustrated in Figures 2B - 2I, other configurations of the electrode 32 provide fluid communication between the first region 31 and the second region 33. Figure 2B schematically illustrates a cylindrically-shaped electrode 32 with open ends and louvered openings along its sides. Figure 2C schematically illustrates a cylindrically-shaped electrode 32 with open ends and solid sides. Figure 2D schematically illustrates an electrode 32 comprising a series of colinear cylindrically-shaped segments with open ends and solid sides. Figure 2E schematically illustrates an electrode 32 with a partial cylindrical shape, open ends and solid sides. Figure 2F schematically illustrates a cylindrically-symmetric and longitudinally-asymmetric electrode 32 with open ends and solid sides. Figure 2G schematically illustrates an asymmetric electrode 32 with open ends and solid sides. More than one electrode can be used to generate the plasma. Figure 2H schematically illustrates an electrode system with a first electrode 32 that is cylindrically-shaped with open ends and solid sides, and a second electrode 32' comprising a wire substantially colinear with the first electrode 32. The LF voltage is applied between the first electrode 32 and the second electrode 32'. In this embodiment, the first region 31 is the region between the first electrode 32 and the second electrode 32', and the second region 33 is between the first electrode 32 and the vacuum chamber 12. Figure 2I schematically illustrates a generally square or rectangular electrode within a generally square or rectangular vacuum chamber. The various configurations for generally cylindrical electrodes schematically illustrated in Figures 2A-2H can also be applied to the generally square or rectangular electrode of Figure 2I. Each of these embodiments

of the electrode 32 provide fluid communication between the first region 31 and the second region 33.

The vacuum pump 14 of the preferred embodiment is coupled to the vacuum chamber 12 via the vacuum pump line 15 and the vacuum valve 16. Both the vacuum pump 14 and the vacuum pump valve 16 are coupled to, and controlled by, the process control module 30. By opening the vacuum valve 16, gases within the vacuum chamber 12 are pumped out of the vacuum chamber 12 through the vacuum pump line 15 by the vacuum pump 14. In certain embodiments, the vacuum valve 16 is capable of being opened to variable degrees to adjust and control the pressure in the vacuum chamber 12.

The reactive agent source 18 of the preferred embodiment is a source of fluid coupled to the vacuum chamber 12 via the reactive agent line 19 and the reactive agent valve 20. The reactive agent valve 20 is coupled to, and controlled by, the process control module 30. The reactive agent source 18 of the preferred embodiment comprises reactive agent species. In the preferred embodiment, the reactive agent species comprises a germicide which is a sterilant or a disinfectant, such as hydrogen peroxide. In addition, the germicide supplied by the reactive agent source 18 can be in gas or vapor form. By opening the reactive agent valve 20, reactive agent atoms and molecules from the reactive agent source 18 can be transported into the vacuum chamber 12 via the reactive agent line 19. In certain embodiments, the reactive agent valve 20 is capable of being opened to variable degrees to adjust the pressure of the reactive agent in the vacuum chamber 12. In the exemplary embodiment of the present invention, the reactive agent species of the reactive agent source 18 comprising hydrogen peroxide molecules.

The vent 26 of the preferred embodiment is coupled to the vacuum chamber 12 via the vent line 27 and the vent valve 28. The vent valve 28 is coupled to, and controlled by, the process control module 30. By opening the vent valve 28, vent gas is vented into the vacuum chamber 12 via the vent line 27. In certain embodiments, the vent valve 28 is capable of being opened to variable degrees to adjust the pressure of the air in the vacuum chamber 12. In the exemplary embodiment of the present invention, the vent 26 is a High Efficiency Particulate-filtered Air (HEPA) vent which provides

filtered air as the vent gas. Other vent gases compatible with the present invention include, but are not limited to, dry nitrogen, and argon.

The process control module 30 is coupled to various components of the sterilization system 10 to control the sterilization system 10. In an exemplary embodiment of the present invention, the process control module 30 is a microprocessor configured to provide control signals to the various other components in response to the various signals received from other components.

The LF power module 22 of the preferred embodiment is coupled to the electrode 32 via the LF voltage conduit 24, and is coupled to, and controlled by, the process control module 30. The LF power module 22 is adapted to apply a low frequency voltage between the electrode 32 and the vacuum chamber 12 so as to generate a plasma in the vacuum chamber 12. Figure 3, which is broken into Figures 3a and 3b, schematically illustrates an embodiment of the LF power module 22 compatible with the phase angle control method of controlling the low frequency power applied to the plasma. As illustrated in Figure 3, the LF power module 22 comprises an over-power relay 40, a pair of metal oxide varistors 42, a step-up transformer 50, a flyback current shunt element 62, an inductor 64, a capacitor 66, and a LF power feedback control system 70. The LF power feedback control system 70 illustrated in Figure 3 comprises a power controller 60, a current monitor 80, a voltage monitor 90, and a power monitor 100 coupled to the current monitor 80 and the voltage monitor 90. Line voltage (typically 200 - 240 VAC, 50/60 Hz) is provided to the step-up transformer 50 via the closed over-power relay 40 which is coupled to the LF power feedback control system 70.

In the embodiment illustrated in Figure 3, the metal oxide varistors (MOVs) 42 are used to suppress transient voltage impulses. Each MOV 42 is a multiple-junction solid-state device capable of withstanding large magnitude impulses with a low amount of let-through voltage. The MOVs 42 serve as fast acting "variable resistors" with a low impedance at higher-than-normal voltages and a high impedance at normal voltages. MOVs are manufactured for specific voltage configurations and for a variety of impulse magnitudes. Persons skilled in the art are able to select MOVs 42 consistent with the present invention.

The output voltage of the step-up transformer 50 is preferably between approximately 100 and 1000 V_{rms} , more preferably between approximately 200 and 500 V_{rms} , and most preferably between approximately 250 and 450 V_{rms} . The output voltage of the step-up transformer 50 is transmitted to the power controller 60, which provides the LF voltage to the electrode 32 and vacuum chamber 12 via the flyback current shunt element 62, the inductor 64, the capacitor 66, and the LF power feedback control system 70. The flyback current shunt element 62 provides a path for fly-back current and to tune the circuit, and in the preferred embodiment the flyback current shunt element 62 is a load resistor of approximately 1500 ohms. In other embodiments, the flyback current shunt element 62 can be a snubber. The inductance of the inductor 64 is chosen to limit noise spikes in the LF current, and is typically approximately 500 mH. The capacitance of the capacitor 66 is chosen to maximize the efficiency of power transfer to the LF plasma by matching the resonant frequency of the series LC circuit to the frequency of the applied LF voltage. For a 60 Hz voltage and an inductance of 500 mH, a capacitance of approximately 13.6 μF provides the resonant condition for which the impedance of the series LC circuit is approximately zero, thereby maximizing the transmitted LF power. Persons skilled in the art are able to select appropriate values for these components depending on the frequency of the applied LF voltage in a manner compatible with the present invention.

Figure 4, which is broken into Figures 4a and 4b, schematically illustrates an embodiment of the LF power module 22 compatible with the amplitude control method of controlling the low frequency power applied to the plasma. As illustrated in Figure 4, the LF power module 22 comprises an over-power relay 40, a pair of metal oxide varistors 42, a step-up transformer 55, and a LF power feedback control system 70. The LF power feedback control system 70 illustrated in Figure 4 comprises a high voltage (HV) DC power supply 51, a voltage-controlled oscillator (VCO) 52, a voltage-controlled amplifier (VCA) 53, a HV operational amplifier 54, a current monitor 80, a voltage monitor 90, and a power monitor 100 coupled to the current monitor 80 and the voltage monitor 90. Line voltage is provided to the HV DC power supply 51 via the closed over-power relay 40 which is coupled to the LF power feedback control system 70. The output of the HV DC power supply 51 is preferably between approximately

100 and 1000 VDC, more preferably between approximately 200 and 500 VDC, and most preferably between approximately 250 and 450 VDC.

In the embodiment illustrated in Figure 4, the VCO 52 generates a sinewave output with a constant amplitude and fixed low frequency less than or equal to approximately 200 kHz (which includes DC voltages and currents), the low frequency selected by supplying an appropriate set-point voltage to the VCO 52. Alternative embodiments can utilize other waveforms, e.g., triangular or square waveforms. The LF output of the VCO 52 is supplied to the VCA 53, which serves as a power controller to maintain a substantially stable average LF power applied to the plasma. In response to a feedback signal from the power control module 110, the VCA 53 amplifies the LF output of the VCO 52 to generate an amplified LF voltage with an amplitude between approximately 0 and 12 VAC. The amplified LF voltage from the VCA 53 is supplied to the HV operational amplifier 54 which in response generates a high voltage LF output with an amplitude determined by the amplitude of the amplified LF voltage from the VCA 53. Appropriate HV operational amplifiers are commercially available (e.g., Apex Microtechnology, Tuscon, AZ, part number PA93), and persons skilled in the art are able to select a HV operational amplifier compatible with the present invention. Typically, the amplitude of the high voltage LF output from the HV operational amplifier 54 is approximately 100 to 150 VAC. In order to generate larger amplitude LF voltages to be applied to the plasma, the high voltage LF output from the HV operational amplifier 54 can be further amplified by the step-up transformer 55, as illustrated in Figure 4. Alternatively, the step-up transformer 55 may be omitted if the HV operational amplifier 54 is capable of generating a high voltage LF output with the desired amplitude to be applied to the plasma.

In both the phase angle control embodiment illustrated in Figure 3 and the amplitude control embodiment illustrated in Figure 4, the LF power feedback control system 70 of the LF power module 22 further comprises a power control module 110 coupled to the power monitor 100, which is coupled to the current monitor 80 and voltage monitor 90. The current monitor 80 measures the LF current through the electrode 32 and the vacuum chamber 12. In the preferred embodiment of the present invention, the current monitor 80 includes a current sensor 82 which provides a voltage

output indicative of the measured real-time, cycle-by-cycle LF current, a first converter 84 which produces a DC voltage in response to the RMS of the voltage output of the current sensor 82, and a first voltage amplifier 86 which amplifies the DC voltage from the first converter 84 to produce a real-time current signal. In addition, the current monitor 80 also includes an over-current detector 88, which monitors the DC voltage from the first converter 84 in real-time and sends an error signal to the power control module 110 if the LF current exceeds a pre-set value, caused for example by a plasma instability between the electrode 32 and the vacuum chamber 12. Under such an occurrence, the LF voltage is turned off momentarily. This occurrence can result in a few cycles being lost, however the LF power is stabilized so that the average power is not affected by more than a predetermined tolerance.

The voltage monitor 90 measures the LF voltage between the electrode 32 and the vacuum chamber 12. In the preferred embodiment of the present invention, the voltage monitor 90 includes a step-down transformer 92 which produces a voltage output indicative of the measured real-time, cycle-by-cycle LF voltage, a second converter 94 which produces a DC voltage in response to the RMS of the voltage output of the step-down transformer 92, and a second voltage amplifier 96 which amplifies the DC voltage from the second converter 94 to produce a real-time voltage signal. In other embodiments, the voltage output from the step-down transformer 92 and the voltage output of the current sensor 82 are multiplied together and directed to a single converter which creates a voltage signal corresponding to the power applied to the plasma.

In the preferred embodiment, the power monitor 100 further comprises a multiplier that receives the DC voltages from the current monitor 80 and the voltage monitor 90, and multiplies these two voltages to produce a real-time power signal proportional to the LF power applied to the plasma between the electrode 32 and the vacuum chamber 12, the real-time power signal being generated in response to the real-time current and real-time voltage signals, and transmitted to the power control module 110. In other embodiments, the power monitor 100 monitors the LF power applied to the plasma by utilizing a signal indicative of the real-time impedance of the plasma with either the real-time current or real-time voltage signals. In still other embodiments, the power monitor 100 monitors the LF power applied to the plasma by utilizing other real-

time signals which indirectly indicate the LF power applied to the plasma; e.g., a real-time signal proportional to the brightness of the glow discharge generated by the plasma. Persons skilled in the art can select an appropriate power monitor 100 compatible with the present invention.

5 The power control module 110 of the preferred embodiment includes a fault detector, such as an over-power detector 112 which monitors the real-time power signal from the power monitor 100 and opens the over-power relay 40 if the LF power exceeds a pre-set value, thereby extinguishing the LF plasma. After such an occurrence, the control of restart can be given to the user or to software. The power control module 110
10 of the preferred embodiment further comprises an additional fault detector, such as a thermal switch 114 which detects overheating, and a power control processor 120.

In the preferred embodiment, the power control processor 120 controls and monitors the status of the LF power feedback control system 70. The power control processor 120 is coupled to a user interface 122 which provides user input regarding a
15 selected power magnitude setting and a selected power on/off setting. The power control processor 120 is also coupled to the power monitor 100, the thermal switch 114, and the over-current detector 88. In the preferred embodiment, the power magnitude setting can be selected from two power levels. When the LF power is turned on, the preferred embodiment of the power control processor 120 ensures that a "soft start"
20 condition is maintained in which the inrush current is minimized. In addition, the user interface 122 receives signals from the power control processor 120 indicative of the status of the sterilization system 10, which is communicated to the user.

In the phase angle control embodiment illustrated in Figure 3, the power control processor 120 is also coupled to the power controller 60. In this embodiment, the power
25 control processor 120 transmits a signal to the power controller 60 in response to signals from the user interface 122, power monitor 100, over-current detector 88, and thermal switch 114 in order to maintain a substantially stable LF power applied to the LF plasma while avoiding error conditions. In the amplitude control embodiment illustrated in Figure 4, the power control processor 120 is coupled to the VCA 53. In
30 this embodiment, the power control processor 120 transmits a signal to the VCA 53 in response to signals from the user interface 122, power monitor 100, over-current

detector 88, and thermal switch 114 in order to maintain a substantially stable LF power applied to the LF plasma while avoiding error conditions. In both embodiments illustrated in Figure 3 and Figure 4, the power control processor 120 typically maintains the LF power applied to the LF plasma within a tolerance of approximately 0 - 5% of the specified power level.

Note that not all of the components listed and described in Figure 3 and Figure 4 are required to practice the present invention, since Figure 3 and Figure 4 merely illustrate particular embodiments of the LF power module 22. These components include components for automation, safety, regulatory, efficiency, and convenience purposes. Other embodiments compatible with the present invention can eliminate some or all of these components, or can include additional components.

In response to the signal from the power control processor 120, the power controller 60 of the embodiment illustrated in Figure 3 controls the LF power applied between the electrode 32 and the vacuum chamber 12 by utilizing phase angle control. Under phase angle control, the duty cycle of the LF power is modified by zeroing the voltage and current applied between the electrode 32 and the vacuum chamber 12 for a portion Δ of the cycle period. Such phase angle control is often used to maintain constant power from electric heaters or furnaces. Figure 5A schematically illustrates the voltage and current for a 100% duty cycle (*i.e.*, $\Delta = 0$) and for a reduced duty cycle (*i.e.*, $\Delta \neq 0$). During normal operations, the power controller 60 maintains a constant LF power applied to the plasma by actively adjusting the duty cycle of the LF power in response to the feedback real-time signal received from the power control module 110 in response to the measured LF power. When a fault event is detected by the over-current detector 88 or thermal switch 114, the power control processor 120 reduces the LF power by reducing the duty cycle of the LF power, and it transmits a signal to the user interface 122 to provide notification of the fault event. Persons skilled in the art are able to select appropriate circuitry to modify the duty cycle of the LF power consistent with the present invention.

Alternatively, the LF power can be controlled by utilizing amplitude control, as in the embodiment illustrated in Figure 4. Under amplitude control, the LF power is modified by adjusting the amplitude of the voltage and current applied between the

electrode 32 and the vacuum chamber 12. Figure 5B schematically illustrates the voltage and current corresponding to a first LF power setting and a second LF power setting less than the first LF power setting. During normal operations, the VCA 53 maintains a constant LF power applied to the plasma by actively adjusting the amplitude of the LF power in response to the feedback real-time signal received from the power control module 110 in response to the measured LF power. Persons skilled in the art are able to select appropriate circuitry to modify the amplitude of the LF power consistent with the present invention.

The electronics for RF sterilizers are complicated by the need of such systems to attempt to closely match the output impedance of the RF generator with the plasma impedance at all times in order to maximize power efficiency and to avoid damage to the RF generator. Plasma impedance varies widely during plasma formation, being very high until the plasma is fully formed, and very low thereafter. When first igniting a plasma, the RF generator cannot match the high plasma impedance which exists prior to the full formation of the plasma, so a large fraction of the power output is reflected back to the RF generator. RF generators have protection systems which typically limit the RF generator output during periods of high reflected power to avoid damage. However, to ignite the plasma, the voltage output of the RF generator must exceed the threshold voltage required for plasma ignition. The threshold voltage is dependent on the chamber pressure, reactive agent, and other operating geometries and parameters and is approximately 300 V_{rms} in the preferred embodiment. In an RF system, once ignition has been achieved, and the plasma impedance is thereby reduced, the magnitude of the applied RF voltage must be reduced to a sustaining voltage, e.g., approximately 140 V_{rms}, to avoid excessive power delivery. Because the higher RF voltages required for plasma ignition produce excessively high reflected power before full plasma formation, RF generators require complicated safeguards to prevent damage during the plasma ignition stage.

Conversely, the complexity of the power system and rate of ignition failures are significantly reduced for LF sterilizers since the LF sterilizers may operate using applied voltages above the threshold voltage and have much less restrictive output impedance matching requirements. For frequencies below approximately 1 kHz, during

the times at which the applied LF voltage equals zero, as seen in Figure 5A, the LF plasma is extinguished and there is no LF plasma in the vacuum chamber. The LF plasma must then be re-ignited twice each cycle. By only operating in one voltage regime, LF sterilizers have simpler and more reliable electrical systems than do RF sterilizers. These electrical systems are easier to service and diagnose, thereby reducing the costs associated with repair. In addition, the higher peak plasma densities resulting from LF sterilizers likely result in increased dissociative recombination on the articles, thereby reducing the amount of residual reactive species remaining on the articles after the sterilization procedure.

In certain embodiments, localized gas heating causes reductions of the plasma impedance, which then generate arcing or other plasma instabilities. This condition is more likely to occur where current densities are larger. However, this effect is reduced, and stability is increased, for frequencies higher than the 50/60 Hz of the incoming line voltage. As schematically illustrated in Figure 6, which is broken into Figures 6a and 6b, certain embodiments of the LF power module 22 may also include a switching module 130 to provide higher frequencies by pulsating the LF power applied to the plasma. While Figure 6 is based on the embodiment illustrated in Figure 3, a switching module 130 can also be used by making a similar modification to the embodiment of Figure 4. While Figure 6 shows the switching module 130 inserted between the first MOV 42 and the step-up transformer 50, persons skilled in the art appreciate that other embodiments can have the switching module 130 at other locations within the LF power module 22.

Figure 7 schematically illustrates the output from a switching module 130 compatible with the present invention. As shown in Figure 7, an incoming sinusoidal voltage with a frequency of 60 Hz is pulsated by the switching module 130 to form a series of voltage pulses with widths W and spaced by times T . Persons skilled in the art appreciate that other waveforms may also be inputted into the switching module 130. For example, in order to minimize or eliminate periods in which the applied voltage is less than the threshold voltage V_T required for plasma ignition, a rippled DC voltage can be generated by full-wave-rectifying and filtering the line voltage prior to pulsating the voltage via the switching module 130, as illustrated in Figure 8a. In one embodiment,

such a rippled DC voltage can be generated by inserting a AC-to-DC converter in the device schematically illustrated by Figure 6 between the over power relay 40 and the MOV 42. Persons skilled in the art can identify other embodiments which can generate such a rippled DC voltage.

5 For illustrative purposes, the output of the switching module 130 illustrated in Figure 7 has a frequency of approximately 1000 Hz. Persons skilled in the art appreciate that other frequencies are compatible with the present invention. The output frequency of the switching module is preferably less than or equal to approximately 200 kHz (which includes DC voltages and currents), more preferably between
10 approximately 1 kHz to 100 kHz, and most preferably between approximately 20 kHz to 50 kHz. In addition, the switching module 130 can be configured to provide an output with unipolar pulsation, as illustrated in Figure 8b, or with bipolar pulsation, as illustrated in Figure 8c. Bipolar pulsation reduces the possibility of electrode sputtering by the plasma and can provide a more stable plasma. Figure 9 schematically illustrates
15 one embodiment of a switching module 130 which generates a unipolar pulsation by utilizing a bridge rectifier 131, a power MOSFET 132, a MOSFET driver 133, a snubber 134, a opto-isolator 135, and a function generator 136. The snubber 134 is used to shunt the energy stored in the leakage inductance of the step-up transformer 50 so it does not damage the power MOSFET 132. An example of an opto-isolator 135
20 compatible with the present invention is the 4N26 phototransistor optocoupler, sold by Texas Instruments of Dallas, Texas. An example of a power MOSFET 132 compatible with the present invention is the "Super-247," serial number IRFPS37N50A, sold by International Rectifier of El Segundo, California. An example of a MOSFET driver 133 compatible with the present invention is the SN75372 dual MOSFET driver, sold by
25 Texas Instruments of Dallas, Texas.

In certain embodiments, such as that illustrated in Figure 9, the LF power applied to the plasma can also be adjusted by the switching module 130 by adjusting pulse widths W or times T between pulses. In certain embodiments, the function generator 136 can be replaced by a pulse width modulation (PWM) controller that
30 automatically controls the applied LF power. While the period (W+T) is the inverse of the selected pulsating frequency, the ratio of W/T can be varied to control the average

LF power applied to the plasma. In such embodiments, the switching module 130 can receive appropriate signals from the power control processor 120 to appropriately select the pulse widths W and/or times T.

Figure 10 schematically illustrates a preferred method of sterilization using the apparatus schematically illustrated in Figure 1. The sterilization process shown in Figure 10 is exemplary, and persons skilled in the art recognize that other processes are also compatible with the present invention. The preferred process begins by sealing 200 the article to be sterilized into the vacuum chamber 12. The vacuum chamber is then evacuated 210 by engaging the vacuum pump 14 and the vacuum valve 16 under the control of the process control module 30. The vacuum chamber 12 is preferably evacuated to a pressure of less than approximately 1320 Pa (10 Torr), more preferably between approximately 25 to 270 Pa (0.2 to 2 Torr), and most preferably between approximately 40 to 200 Pa (0.3 to 1.5 Torr).

In an exemplary process, upon reaching a desired pressure in the vacuum chamber 12, the process control module 30 signals the LF power module 22 to energize the electrode 32 within the vacuum chamber 12. By applying a LF voltage to the electrode 32, the LF power module 22 ionizes the residual gases in the vacuum chamber 12, thereby creating 220 a gas discharge LF plasma inside the vacuum chamber 12. This gas discharge LF plasma is formed from the residual gases in the vacuum chamber 12, which are primarily air and water vapor. Because this gas discharge LF plasma is created 220 before the reactive agent is injected into the vacuum chamber 12, this gas discharge LF plasma is typically called the “pre-injection” plasma. The vacuum valve 14 is controllably opened and closed to maintain a preset vacuum pressure during the pre-injection plasma step 220. The pre-injection plasma heats the surfaces inside the vacuum chamber 12, including the articles, thereby aiding the evaporation and removal of condensed water and other absorbed gases from the vacuum chamber 12 and the articles. A similar pre-injection plasma is described by Spencer, et al. in U.S. Patent Nos. 5,656,238 and 6,060,019, which are incorporated by reference herein. In an exemplary process, the pre-injection plasma is turned off after approximately 0 to 60 minutes. Other embodiments that are compatible with the present invention do not include the creation of the pre-injection plasma, or use multiple pre-injection plasmas.

In still other embodiments, the vacuum chamber 12 can be vented after the articles are exposed to the pre-injection plasma.

In the preferred process, upon reaching a desired chamber pressure, the vacuum valve 16 is closed, and the reactive agent valve 20 is opened under the control of the process control module 30, thereby injecting 230 reactive agent from the reactive agent source 18 into the vacuum chamber 12 via the reactive agent line 19. In the preferred embodiment, the reactive agent comprises hydrogen peroxide, which is injected in the form of a liquid which is then vaporized. The injected liquid contains preferably from about 3% to 60% by weight of hydrogen peroxide, more preferably from about 20% to 60% by weight of hydrogen peroxide, and most preferably from about 30% to 60% by weight of hydrogen peroxide. The concentration of hydrogen peroxide vapor in the vacuum chamber 12 may range from 0.125 to 20 mg of hydrogen peroxide per liter of chamber volume. The higher concentrations of hydrogen peroxide will result in shorter sterilization times. Air or inert gas such as argon, helium, nitrogen, neon, or xenon may be added to the chamber with the hydrogen peroxide to maintain the pressure in the vacuum chamber 12 at the desired level. This injection 230 of reactive agent may occur as one or more separate injections.

Due to this injection 230 of reactive agent, the chamber pressure of the preferred process rises to approximately 2000 Pa (15 Torr) or more. After approximately 6 minutes into the injection stage 230, the reactive agent is permitted to diffuse 240 completely and evenly throughout the vacuum chamber 12. After approximately 1 - 45 minutes of diffusing 240, the reactive agent is substantially in equilibrium inside the vacuum chamber 12. This diffusing 240 allows the reactive species to diffuse through the packaging material of the articles, and come into close proximity, if not contact, with the surfaces of the articles, thereby sterilizing the articles. In other embodiments, the diffusion of the reactive agent can be immediately followed by a vent of the vacuum chamber 12.

The vacuum chamber 12 is then partially evacuated 250 by pumping out a fraction of the reactive agent from the vacuum chamber 12 by controllably opening the vacuum valve 16 under the control of the process control module 30. Once the vacuum pressure within the vacuum chamber 12 has reached the desired pressure, the vacuum

valve 16 is controllably adjusted to maintain the desired pressure, and the process control module 30 signals the LF power module 22 to energize the electrode 32 within the vacuum chamber 12. In the preferred embodiment in which the reactive agent comprises hydrogen peroxide, the pressure of the hydrogen peroxide in the vacuum chamber 12 is preferably less than approximately 1320 Pa (10 Torr), more preferably between approximately 25 and 270 Pa (0.2 to 2 Torr), and most preferably between approximately 40 and 200 Pa (0.3 to 1.5 Torr). By applying a LF voltage to the electrode 32, the LF power module 22 generates a reactive agent LF plasma inside the vacuum chamber 12 by ionizing the reactive agent. The article is exposed to the reactive agent LF plasma for a controlled period of time. In the preferred embodiment, an additional cycle 275 is performed. Other embodiments may omit this additional cycle 275, or may include further cycles.

In both RF and LF plasmas, the components of the reactive agent plasma include dissociation species of the reactive agent and molecules of the reactive agent in excited electronic or vibrational states. For example, where the reactive agent comprises hydrogen peroxide as in the preferred embodiment, the reactive agent plasma likely includes charged particles such as electrons, ions, various free radicals (e.g., OH, O₂H), and neutral particles such as ground state H₂O₂ molecules and excited H₂O₂ molecules. Along with the ultraviolet radiation produced in the reactive agent plasma, these reactive agent species have the potential to kill spores and other microorganisms.

Once created, the charged particles of the reactive agent plasma are accelerated by the electric fields created in the vacuum chamber 12. Because of the fluid communication between the first region 31 and the second region 33, some fraction of the charged particles created in the first region 31 are accelerated to pass from the first region 31 to the second region 33 which contains the articles.

Charged particles passing from the first region 31 to the second region 33 have their trajectories and energies affected by the electric potential differential of the sheath regions between the plasma and the walls of the vacuum chamber 12 and the electrode 32. These sheath regions are created by all electron-ion plasmas in contact with material walls, due to charged particles impinging from the plasma onto the walls. Electrons, with their smaller mass and hence greater mobility, are lost from the plasma

to the wall before the much heavier and less mobile ions, thereby creating an excessive negative charge density surrounding the walls and a corresponding voltage differential which equalizes the loss rates of the electrons and the ions. This voltage differential, or sheath voltage, accelerates electrons away from the wall surface, and accelerates positive ions toward the wall surface.

The sheath voltage varies for different plasma types, compositions, and methods of production. For RF plasmas, the sheath voltage is typically 40% - 80% of the RF voltage applied to the electrode 32. For example, for a root-mean-squared (RMS) RF voltage of 140 V_{rms} applied to the electrode 32 once the RF plasma is established, the corresponding sheath voltage is approximately 55 - 110 V. An ion entering the sheath region surrounding the electrode 32 will then be accelerated to an energy of 55 - 110 eV. This acceleration of positive ions by the sheath voltage is the basic principle behind semiconductor processing by RF plasmas.

As described above, for the LF plasmas of the preferred embodiment of the present invention, the voltage applied to the electrode 32 may be equal to or greater than the ignition threshold voltage, which is typically 300 V. In addition, for LF plasmas, the sheath voltage is typically a higher percentage of the applied voltage than for RF plasmas, so the sheath voltage of the preferred embodiment of the present invention is then much higher than the sheath voltage for an RF plasma system. This higher sheath voltage thereby accelerates the charged particles of the LF plasma to much higher energies. Therefore, because the charged particles are accelerated to higher energies, the charged particles of the LF plasma of the preferred embodiment travel farther and interact more with the articles than do the charged particles of RF plasma sterilizers.

Since the LF electric field changes polarity twice each cycle, the direction of the electric field acceleration on the charged particles reverses twice each cycle. For charged particles in the first region 31, this oscillation of the direction of the acceleration results in an oscillation of the position of the charged particles. However, because of the fluid communication between the first region 31 and the second region 33, some fraction of the charged particles are able to pass to the second region 33 containing the articles from the first region 31 before the direction of the electric field acceleration reverses.

The fraction of the charged particles created in the reactive agent LF plasma which enter the second region 33 is a function of the frequency of the applied electric field. The charged particles have two components to their motion -- random thermal speed and drift motion due to the applied electric field. The thermal speed, measured by the temperature, is the larger of the two (typically approximately $10^7 - 10^8$ cm/sec for electrons), but it does not cause the charged particles to flow in any particular direction. Conversely, the drift speed is directed along the electric field, resulting in bulk flow of charged particles in or opposed to the direction of the applied electric field. The magnitude of the drift speed is approximately proportional to the magnitude of the applied electric field, and inversely proportional to the mass of the charged particle. In addition, the magnitude of the drift speed is dependent on the gas species and chamber pressure. For example, for typical operating parameters of gas discharge plasma sterilizers, including an average electric field magnitude of approximately 1 volt/cm, the drift speed for an electron formed in a gas discharge plasma is typically approximately 10^6 cm/sec.

A charged particle enters the second region 33 containing the articles only if it reaches the second region 33 before the polarity of the applied electric field changes, which would reverse the acceleration of the charged particle away from the electrode 32. For example, for an applied RF electric field with a frequency of 13.56 MHz, the period of the electric field is approximately 7.4×10^{-8} sec, so an electron only moves a distance of approximately 3.7×10^{-3} cm during the half-cycle or half-period before the direction of the electric field changes and the electron is accelerated away from the electrode 32. Due to their much larger masses, ions move much less than do electrons. Where the first region 31 between the vacuum chamber 12 and the electrode 32 is approximately 2.54 cm wide, as in the preferred embodiment, only a fraction of the charged particles created by an RF plasma would actually reach the second region 33 containing the articles.

Conversely, for an applied LF electric field with a frequency of 60 Hz, the period of the electric field is approximately 16.7×10^{-3} sec, so an electron can move approximately 8.35×10^3 cm before it is accelerated away from the electrode 32. Therefore, the use of LF voltages to create the plasma in the sterilization system 10 of

the preferred embodiment results in more activity in the second region 33, as compared to a plasma generated using RF voltages. This higher activity in LF sterilizers likely contributes to the increased efficiency for the removal of residual reactive species from the sterilized articles as compared to RF sterilizers.

5 The plasma decay time, defined as a characteristic time for the plasma to be neutralized after power is no longer applied, provides an approximate demarcation between the LF and RF regimes. The plasma decay time is not known precisely, but it is estimated to be approximately 10^{-4} - 10^{-3} sec for the plasma densities used in sterilizer systems, such as the preferred embodiment of the present invention. This plasma decay
10 time corresponds to the time a charged particle exists before it is neutralized by a collision with a surface or another plasma constituent, and is dependent on the plasma species generated and the geometries of the various components of the sterilization system 10. As described above, the LF regime is characterized by a plasma which is extinguished and re-ignited twice each cycle, i.e., the half-period of the applied LF
15 voltage is greater than the plasma decay time. Therefore, the sterilization system 10 is continually run at an applied voltage above the ignition threshold voltage of the plasma in order to re-ignite the plasma. The estimated approximate range of plasma decay times of 10^{-4} - 10^{-3} sec for many of the plasmas compatible with the present invention then translates to an upper limit on the low frequency regime of approximately
20 1 - 10 kHz. However, under certain circumstances, higher frequencies can be tolerated.

 Alternatively, the upper limit of the low frequency regime may be defined as the frequency at which the electron drift speed is too slow for an electron to traverse the 2.54-cm-wide first region 31 during a half-period of the applied LF voltage. Under
25 typical operating geometries, this upper limit of the low frequency regime would be approximately 200 kHz. For other geometries, the upper limit of the low frequency regime can be correspondingly different.

 In the preferred method, the LF power module 22 remains energized for approximately 2 - 15 minutes, during which the plasma removes excess residual
30 reactive species present on surfaces within the vacuum chamber 12, including on the articles. There is a brief rise of the vacuum pressure upon generating 260 the plasma, however, the majority of the residual removal step 270 is conducted at an approximately

constant vacuum pressure of 50 to 70 Pa (0.4 to 0.5 Torr). The residual removal step 270 is ended by the process control module 30, which turns off the LF power module 22, thereby quenching the plasma.

After the residual removal step 270, the vacuum chamber 12 is vented 280 by the process control module 30 which opens the vent valve 28, thereby letting in vent gas from the vent 26 through the vent line 27 and the vent valve 28. In the preferred process, the vacuum chamber 12 is then evacuated 290 to a pressure of approximately 40 to 105 Pa (0.3 to 0.8 Torr) to remove any remaining reactive agent which may be present in the vacuum chamber 12. The vacuum chamber 12 is then vented again 300 to atmospheric pressure, and the sterilized articles are then removed 310 from the vacuum chamber 12.

The LF plasma provides a reduction of the amount of residual reactive agent molecules remaining on the articles after the sterilization procedure is complete. Where the reactive agent comprises hydrogen peroxide, the amount of residual hydrogen peroxide remaining on the sterilized articles is preferably less than approximately 8000 ppm, more preferably less than approximately 5000 ppm, and most preferably less than approximately 3000 ppm. In a comparison of the amount of residual hydrogen peroxide remaining after a LF plasma sterilization as compared to a RF plasma sterilization, nine polyurethane test samples were exposed to hydrogen peroxide during a simulated sterilization cycle in both a LF sterilizer and a RF sterilizer. Each sample was prepared by washing with Manuklenz® and drying prior to sterilization to avoid any cross contamination. The nine samples were then distributed uniformly across the top shelf of a standard industrial rack.

A full LF sterilization cycle, which matched nearly exactly the conditions of a standard RF sterilizer cycle, was used to perform the comparison. The full LF sterilization cycle included a 20-minute exposure to a pre-injection plasma, a first 6-minute hydrogen peroxide injection, a vent to atmosphere, a 2-minute diffusion, a first 2-minute post-injection plasma, a second 6-minute hydrogen peroxide injection, a vent to atmosphere, a 2-minute diffusion, a second 2-minute post-injection plasma, and a vent to atmosphere. Two full LF sterilization cycles were performed and compared to

two full RF sterilization cycles. As seen in Table 1, all parameters other than the post-injection plasma power were maintained as constant as possible from run to run.

Table 1:

	LF Run 1	LF Run 2	RF Run 1	RF Run 2
Pre-injection plasma power	727 W	779 W	751 W	752 W
First post-injection plasma power	783 W	874 W	757 W	756 W
Second post-injection plasma power	755 W	893 W	758 W	758 W
Chamber temp.	45° C nom.	45° C nom.	45° C nom.	45° C nom.
Injection system temp.	65-75° C	65-75° C	65-75° C	65-75° C
H ₂ O ₂ concentration	17 mg/l	17 mg/l	17 mg/l	17 mg/l
Chamber pressure during plasma	50 Pa (0.4 Torr)	50 Pa (0.4 Torr)	50 Pa (0.4 Torr)	50 Pa (0.4 Torr)

Variations in the pre-plasma power were $\pm 3.5\%$, so the sample temperature was approximately constant from run to run. The samples were then removed and the residual analysis was performed.

The LF sterilizer used to generate the LF plasma was operated at 60 Hz, and with an inductor of 500 mH and a capacitor of 13.6 μ F. LF plasma power was determined by multiplying the voltage across the LF plasma by the current, then averaging on an oscilloscope. The fluctuation level of the LF power was approximately 10%. Table 2 illustrates the results of the comparison.

Table 2:

	LF Run 1	LF Run 2	RF Run 1	RF Run 2
Average post-injection plasma power	769 W	884 W	757 W	757 W
H ₂ O ₂ residuals (ppm)	1973 \pm 144	1864 \pm 75	2682 \pm 317	2510 \pm 203

Exposure to a LF post-injection plasma reduced the residual reactive species more effectively than did exposure to a RF post-injection plasma of comparable power. LF Run 1 had approximately 23% less residual hydrogen peroxide than either RF Run 1 or RF Run 2, even though all had approximately the same post-injection plasma power. The LF processes therefore resulted in less residual hydrogen peroxide than did the corresponding RF process.

5 The comparison of the two LF sterilization cycles illustrates that increased plasma power results in a reduction of the hydrogen peroxide residuals. Furthermore, the variation between samples, as indicated by the standard deviation of the residual measurements, was significantly reduced in the LF process, thereby indicating an increased uniformity as compared to the RF process.

10 Although described above in connection with particular embodiments of the present invention, it should be understood the descriptions of the embodiments are illustrative of the invention and are not intended to be limiting. Various modifications and applications may occur to those skilled in the art without departing from the true spirit and scope of the invention as defined in the appended claims.

11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2187
2188
2189
2190
2191
2192
2193
2194
2195
2196
2197
2198
2199
2200
2201
2202
2203
2204
2205
2206
2207
2208
2209
2210
2211
2212
2213
2214
2215
2216
2217